#### US H5 Ball Bearing Optical Shaft Encoder Page 1 of 5



# Description

The H5 series ball bearing optical shaft encoder has a molded polycarbonate housing and utilizes either a 5-pin or 10-pin finger-latching connector. This non-contacting rotary to digital converter is designed to provide digital feedback information.

The H5 is fully assembled with a brass shaft, two 1/4" ID by 1/2" OD heavy duty ball bearings and a mounting plate. The mounting plate comes with 2 mounting holes for screws #4 or smaller.

A secure connection to the H5 series encoder is made through a 5-pin (singleended versions) or 10-pin (differential versions) finger-latching connector (sold separately). The mating connectors are available from US Digital with several cable options and lengths.

For differential versions: the internal differential line driver (26C31) can source and sink 20mA at TTL levels. The recommended receiver is industry standard 26C32. Maximum noise immunity is achieved when the differential receiver is terminated with a 150  $\Omega$  resistor in series with a .0047  $\mu$  F capacitor placed across each differential pair. The capacitor simply conserves power; otherwise power consumption would increase by approximately 20mA per pair, or 60mA for 3 pairs.



#### Features

- Ball bearing option tracks to 10,000 RPM
- 2-channel quadrature, TTL squarewave outputs
- 3rd channel index option available on some resolutions
- ▶ 32 to 5,000 cycles per revolution (CPR)
- + 128 to 20,000 pulses per revolution (PPR)
- Wide operating temperature
- Single +5VDC supply

# Mechanical Drawing



1400 NE 136th Avenue Vancouver, Washington 98684, USA info@usdigital.com www.usdigital.com







#### **Environmental** $(\bigcirc)$

Parameter	Value	Units
Operating Temperature, CPR < 2000	-40 to 100	С
Operating Temperature, CPR $\geq 2000$	-25 to 100	С
Vibration (5Hz to 2kHz)	20	G
Electrostatic Discharge, IEC 61000-4-2	± 4	kV

RELEASE DATE: 01/21/2016

# Mechanical

Parameter	Value
Max. Acceleration	100000 rad/sec <sup>2</sup>
Max. Shaft Speed	10000 rpm
Max. Shaft Torque	0.05 in-oz
Max. Shaft Loading	2 lbs.
Bearing Life	life in millions of revs. = $(90/P)^3$ where P = radial load in pounds.
Weight	
Single-ended	1.79 oz.
Differential	1.89 oz.

1400 NE 136th Avenue Vancouver, Washington 98684, USA info@usdigital.com www.usdigital.com

# USUBLE H5 Ball Bearing Optical Shaft Encoder Page 3 of 5



Parameter	Value
Max. Shaft Total Indicated Runout	0.006 in.
Moment of Inertia	0.001 oz-in-s <sup>2</sup>
Technical Bulletin TB1001 - Shaft and Bore Tolerances	Download

# Phase Relationship

B leads A for clockwise shaft rotation, and A leads B for counterclockwise rotation viewed from the shaft side of the encoder (see the EM1 page).

### Single-ended Electrical

• Specifications apply over entire operating temperature range.

- + Typical values are specified at Vcc = 5.0Vdc and 25  $^{\circ}$  C.
- For complete details, see the EM1 or EM2 product pages.

Parameter	Min.	Тур.	Max.	Units	Conditions
Supply Voltage	4.5	5.0	5.5	V	
Supply Current		27	33	mA	CPR < 500, no load
		54	62	mA	CPR $\geq$ 500 and <2000, no load
		72	85	mA	$CPR \ge 2000$ , no load
Low-level Output			0.5	V	IOL = 8mA max., CPR < 2000
			0.5	V	$IOL = 5mA max., CPR \ge 2000$
		0.25		V	no load, CPR $\geq 2000$
High-level Output	2.0			V	IOH = -8mA max. and CPR < 2000
	2.0			V	IOH = -5mA max. and CPR $\geq 2000$
		4.8		V	no load and CPR < 2000
		3.5		V	no load and CPR $\geq 2000$
Output Current Per Channel	-8		8	mA	CPR < 2000
	-5		5	mA	CPR ≥ 2000
Output Rise Time		110		nS	CPR < 2000
		50		nS	$CPR \ge 2000, \pm 5mA$ load
Output Fall Time		100		nS	CPR < 2000
		50		nS	$CPR \ge 2000, \pm 5mA$ load

# Differential Electrical

1400 NE 136th Avenue Vancouver, Washington 98684, USA info@usdigital.com www.usdigital.com Local: 360.260.2468 Toll-free: 800.736.0194

Rev. 160201104934

# USUB H5 Ball Bearing Optical Shaft Encoder Page 4 of 5



- Specifications apply over entire operating temperature range.
- <sup>•</sup> Typical values are specified at Vcc = 5.0Vdc and 25  $^{\circ}$  C.
- For complete details, see the EM1 product pages.

Parameter	Min.	Тур.	Max.	Units	Conditions
Supply Voltage	4.5	5.0	5.5	V	-
Supply Current		29	36	mA	CPR < 500, no load
		56	65	mA	$CPR \ge 500$ and < 2000, no load
		74	88	mA	$CPR \ge 2000$ , no load
Low-level Output		0.2	0.4	V	IOL = 20mA max.
High-level Output	2.4	3.4		V	IOH = -20mA max.
Differential Output Rise/Fall Time			15	nS	

### 💮 Pin-out

	10-pin Differential Standard		
Description	Pin	Description	
Ground	1	Ground	
Index	2	Ground	
A channel	3	Index-	
+5VDC power	4	Index+	
B channel	5	A- channel	
	6	A+ channel	
	7	+5VDC power	
	8	+5VDC power	
	9	B- channel	
	10	B+ channel	
	Description Ground Index A channel +5VDC power B channel	10-pin Differential StandardDescriptionPinGround1Index2A channel3+5VDC power4B channel5Index6Index7Index9Index10	



H5 -		-		-	
------	--	---	--	---	--



1400 NE 136th Avenue Vancouver, Washington 98684, USA info@usdigital.com www.usdigital.com





CPR	Index	Output
32 =	NE =No Index	S = Single-ended
50 =	IE =Index	D =Differential
96 =		
100 =		
192 =		
200 =		
250 =		
256 =		
360 =		
400 =		
500 =		
512 =		
540 =		
720 =		
900 =		
1000 =		
1024 =		
1250 =		
2000 =		
2048 =		
2500 =		
4000 =		
4096 =		
5000 =		

#### Notes

- Cables and connectors are not included and must be ordered separately.
- US Digital warrants its products against defects in materials and workmanship for two years.
  See complete warranty for details.



1400 NE 136th Avenue Vancouver, Washington 98684, USA info@usdigital.com www.usdigital.com